

## **CHAPTER - 10**

# **WAVEGUIDES AND CAVITY RESONATORS**

## CHAPTER 10

### WAVEGUIDES AND CAVITY RESONATORS

#### Exercise 10.1

$$l = 2\text{ m}, \quad a = 2\text{ cm}, \quad b = 1\text{ cm}, \quad \text{TM}_{11}, \quad \hat{\gamma}_{11} = j200$$

$$f_{c11} = \frac{3 \times 10^8}{2} \sqrt{\frac{1}{0.02^2} + \frac{1}{0.01^2}} = 6.71 \times 10^9 \text{ Hz}$$

$$\beta_{11} = \frac{\omega}{u_p} \sqrt{1 - \left(\frac{f_{c11}}{f}\right)^2}$$

$$200 = \frac{2\pi f}{3 \times 10^8} \sqrt{1 - \left(\frac{6.71 \times 10^9}{f}\right)^2}$$

$$\text{Solving for } f \text{ yields } f = 1.167 \times 10^{10} \text{ Hz}$$

#### Exercise 10.2

$$\text{At } z = 0 \quad E_{zm} = 2\text{ kV/m}, \quad \hat{\gamma}_{11} = j200, \quad f = 1.167 \times 10^{10} \text{ Hz}, \quad \mu = \mu_0, \quad \epsilon = \epsilon_0$$

$$M = \frac{\pi}{2 \times 10^{-2}} = 50\pi, \quad N = \frac{\pi}{10^{-2}} = 100\pi$$

From Eqs. (10.16) and (10.17),

$$\tilde{E}_z = 2000 \sin(50\pi x) \sin(100\pi y) e^{-j200z}$$

$$E_z(t) = 2000 \sin(50\pi x) \sin(100\pi y) \cos(2\pi \times 1.167 \times 10^{10} t - 200z)$$

$$\tilde{E}_x = \frac{-j200}{(50\pi)^2 + (100\pi)^2} 50\pi \times 2000 \cos(50\pi x) \sin(100\pi y) e^{-j200z}$$

$$\tilde{E}_x = -j5.093 \times 10^2 \cos(50\pi x) \sin(100\pi y) e^{-j200z}$$

$$E_x(t) = 509.3 \cos(50\pi x) \sin(100\pi y) \cos(2\pi \times 1.167 \times 10^{10} t - 200z - \frac{\pi}{2})$$

$$\tilde{E}_y = - \frac{j200}{(50\pi)^2 + (100\pi)^2} (100\pi)(2000) \sin(50\pi x) \cos(100\pi y) e^{-j200z}$$

$$\tilde{E}_y = -j1018.59 \sin(50\pi x) \cos(100\pi y) e^{-j200z}$$

$$E_y(t) = 1018.59 \sin(50\pi x) \cos(100\pi y) \cos(2\pi \times 1.167 \times 10^{10} t - 200z - \frac{\pi}{2})$$

$$\tilde{H}_x = \frac{j1.167 \times 10^{10} \times 2\pi \times 8.85 \times 10^{-12}}{(50\pi)^2 + (100\pi)^2} 100\pi \times 2000 \sin(50\pi x) \cos(100\pi y) e^{-j200z}$$

$$\tilde{H}_x = j3.30 \sin(50\pi x) \cos(100\pi y) e^{-j200z}$$

$$H_x(t) = 3.30 \sin(50\pi x) \cos(100\pi y) \cos(2\pi \times 1.167 \times 10^{10} t - 200z + \frac{\pi}{2})$$

$$\tilde{H}_y = - \frac{j2\pi \times 1.167 \times 10^{10} \times 8.85 \times 10^{-12}}{(50\pi)^2 + (100\pi)^2} 50\pi \times 2000 \cos(50\pi x) \sin(100\pi y) e^{-j200z}$$

$$\tilde{H}_y = -j1.65 \cos(50\pi x) \sin(100\pi y) e^{-j200z}$$

$$H_y(t) = 1.65 \cos(50\pi x) \sin(100\pi y) \cos(2\pi \times 1.167 \times 10^{10} t - 200z - \frac{\pi}{2})$$

### Exercise 10.3

$$a = 1 \text{ cm}, \quad b = 0.5 \text{ cm}, \quad \text{TM}_{11}, \quad f = 9 \text{ GHz}, \quad E_{zm} = 1.5 \text{ kV/m at } z=0$$

$$\epsilon = 2.5\epsilon_0 \quad u_p = \frac{1}{\sqrt{2.5\epsilon_0\mu_0}} = 1.897 \times 10^8 \text{ m/s}$$

$$a) \quad f_{c11} = \frac{1.897 \times 10^8}{2} \sqrt{\left(\frac{1}{10^{-2}}\right)^2 + \left(\frac{1}{5 \times 10^{-3}}\right)^2} = 8.48 \times 10^9 \text{ Hz}$$

$$b) \quad \beta_{11} = \frac{2\pi \times 9 \times 10^9}{1.897 \times 10^8} \sqrt{1 - \left(\frac{8.48 \times 10^9}{9 \times 10^9}\right)^2} = 99.52 \text{ rad/m}$$

$$\hat{\gamma}_{11} = j99.52$$

$$c) u_{p_{11}} = \frac{\omega}{\beta_{11}} = \frac{2\pi \times 9 \times 10^9}{99.52} = 5.68 \times 10^8 \text{ m/s}$$

$$u_{g_{11}} = \frac{(1.897 \times 10^8)^2}{5.68 \times 10^8} = 6.333 \times 10^7 \text{ m/s}$$

$$d) \gamma = \sqrt{\frac{4\pi \times 10^{-7}}{2.5 \times 8.85 \times 10^{-12}}} = 238.32 \Omega$$

$$\gamma_{11} = 238.32 \sqrt{1 - \left(\frac{8.48 \times 10^9}{9 \times 10^9}\right)^2} = 79.83 \Omega$$

$$e) \text{ From Eq. (10.50),}$$

$$\langle P_{11} \rangle = \frac{99.52^2 \times (10^2)^3 (5 \times 10^3)^3}{8 \pi^2 \times 79.83 [(10^2)^2 + (5 \times 10^3)^2]} \times 1500^2$$

$$\langle P_{11} \rangle = 3.53 \times 10^{-3} \text{ W or } 3.53 \text{ mW}$$

#### Exercise 10.4

$$b = 1 \text{ cm}, \quad f = 12 \text{ GHz}, \quad \beta_{10} = 150 \text{ rad/m} \quad \text{TE}_{10}$$

$$150 = \frac{2\pi \times 12 \times 10^9}{3 \times 10^8} \sqrt{1 - \left(\frac{f_{c_{10}}}{12}\right)^2} \Rightarrow f_{c_{10}} = 9.63 \text{ GHz}$$

$$f_{c_{10}} = \frac{u_p}{2a} \Rightarrow a = \frac{3 \times 10^8}{2 \times 9.63 \times 10^9} = 1.557 \times 10^{-2} \text{ m or } a = 1.557 \text{ cm}$$

#### Exercise 10.5

$$a = 1 \text{ cm}, \quad b = 1.5 \text{ cm}, \quad \beta_{01} = 100 \text{ rad/m}$$

$$f_{c_{01}} = \frac{3 \times 10^8}{2 \times 0.015} = 10^{10} \text{ Hz}$$

$$100 = \frac{2\pi f}{3 \times 10^8} \sqrt{1 - \left(\frac{10^{10}}{f}\right)^2} \Rightarrow f = 1.108 \times 10^{10} \text{ Hz}$$

a)

From Eq. (10.62) for  $TE_{01}$ ,

$$\tilde{H}_x = 0, \quad \tilde{E}_y = 0, \quad \tilde{E}_z = 0$$

$$\tilde{E}_x = j \frac{\omega \mu b}{\pi} \hat{H}_{zm} \sin\left(\frac{\pi}{b} y\right) e^{-j\beta_{01} z}$$

$$\tilde{E}_x = \hat{E}_{xm} \sin\left(\frac{\pi}{b} y\right) e^{-j\beta_{01} z}$$

$$\therefore \hat{E}_{xm} = j \frac{\omega \mu b}{\pi} \hat{H}_{zm}$$

$$500 = j \frac{2\pi \times 1.108 \times 10^{10} \times 4\pi \times 10^{-7} \times 1.5 \times 10^{-2} \hat{H}_{zm}}{\pi}$$

$$\hat{H}_{zm} = -j 1.197 \text{ A/m}$$

$$\tilde{E}_x = 500 \sin\left(\frac{\pi}{1.5 \times 10^{-2}} y\right) e^{-j100z} = 500 \sin(209.43y) e^{-j100z}$$

$$E_x(t) = 500 \sin(209.43y) \cos(2\pi \times 1.108 \times 10^{10} t - 100z)$$

$$\tilde{H}_y = j \frac{100 \times 1.5 \times 10^{-2}}{\pi} (-j 1.197) \sin(209.43y) e^{-j100z}$$

$$\tilde{H}_y = 0.5725 \sin(209.43y) e^{-j100z}$$

$$H_y(t) = 0.572 \sin(209.43y) \cos(2\pi \times 1.108 \times 10^{10} t - 100z)$$

$$\tilde{H}_z = -j 1.197 \cos(209.43y) e^{-j100z}$$

$$H_z(t) = 1.197 \cos(209.43y) \cos(2\pi \times 1.108 \times 10^{10} t - 100z - \frac{\pi}{2})$$

$$b) \quad \eta_{01}^{TE} = \frac{377}{\sqrt{1 - \left(\frac{10^{10}}{1.108 \times 10^{10}}\right)^2}} = 875.45 \Omega$$

From Eq. (10.72)

$$\langle P_{01} \rangle = 875.45 \left[ \frac{(100)^2 \times (10^{-2})^3 (1.5 \times 10^{-2})^3 \times 1.197^2}{8 \pi^2 (10^{-2})^2} \right]$$

$$\langle P_{01} \rangle = 5.36 \times 10^{-3} \text{ W} \quad \text{or} \quad 5.36 \text{ mW}$$

### Exercise 10.6

$a = 2 \text{ cm}$ ,  $b = 1 \text{ cm}$ ,  $TE_{10}$ ,  $f = 9 \text{ GHz}$ ,  $E = 20 \text{ V/cm}$  at  $z=0$

$$a) \quad f_{c_{10}} = \frac{3 \times 10^8}{2 \times 0.02} = 7.5 \times 10^9 \text{ Hz} \quad \text{or} \quad 7.5 \text{ GHz}$$

$$b) \quad \beta_{10} = \frac{2\pi \times 9 \times 10^9}{3 \times 10^8} \sqrt{1 - \left(\frac{7.5}{9}\right)^2} = 104.19 \text{ rad/m}$$

$$\hat{\gamma}_{10} = j104.19$$

$$c) \quad \text{Phase velocity: } u_{p_{10}} = \frac{3 \times 10^8}{\sqrt{1 - \left(\frac{7.5}{9}\right)^2}} = 5.43 \times 10^8 \text{ m/s}$$

$$\text{Group velocity: } u_{g_{10}} = 3 \times 10^8 \sqrt{1 - \left(\frac{7.5}{9}\right)^2} = 1.66 \times 10^8 \text{ m/s}$$

$$d) \quad \gamma_{10}^{TE} = \frac{377}{\sqrt{1 - \left(\frac{7.5}{9}\right)^2}} = 682.02 \, \Omega$$

$$e) \quad \langle P_{10} \rangle = 682.02 \frac{104.19^2 \times (2 \times 10^{-2})^3 \times (10^{-2})^3 \times 4.42^2}{8 \pi^2 \times (10^{-2})^2} = 0.147 \text{ W}$$

$$H_{zm} = \frac{20 \times 10^2 \pi}{2\pi \times 9 \times 10^9 \times 4\pi \times 10^{-7} \times 2 \times 10^{-2}}$$

$$H_{zm} = 4.42 \text{ A/m}$$

### Exercise 10.7

$$\epsilon_r = 2.5, \mu_r = 1$$

$$u_p = \frac{1}{\sqrt{2.5 \epsilon_0 \mu_0}} = 1.897 \times 10^8 \text{ m/s}$$

$$a) \quad f_{c_{10}} = \frac{1.897 \times 10^8}{2 \times 0.02} = 4.74 \times 10^9 \text{ Hz}$$

$$b) \quad \beta_{10} = \frac{2\pi \times 9 \times 10^9}{1.897 \times 10^8} \sqrt{1 - \left(\frac{4.74}{9}\right)^2} = 253.4 \text{ rad/m}$$

$$\hat{\gamma}_{10} = j 253.4$$

$$c) \quad u_{p_{10}} = \frac{1.897 \times 10^8}{\sqrt{1 - \left(\frac{4.74}{9}\right)^2}} = 2.23 \times 10^8 \text{ m/s}$$

$$u_{g_{10}} = 1.897 \times 10^8 \sqrt{1 - \left(\frac{4.74}{9}\right)^2} = 1.613 \times 10^8 \text{ m/s}$$

$$d) \quad \eta = \sqrt{\frac{4\pi \times 10^{-7}}{2.5 \times 8.85 \times 10^{-12}}} = 238.32 \Omega$$

$$\eta_{10}^{TE} = \frac{238.32}{\sqrt{1 - \left(\frac{4.74}{9}\right)^2}} = 280.35 \Omega$$

$$e) \quad \langle P_{10} \rangle = 280.35 \frac{253.4^2 \times (2 \times 10^{-2})^3 (10^{-2})^3 4.42^2}{8\pi^2 (10^{-2})^2} = 0.356 \text{ W}$$

### Exercise 10.8

$$\epsilon_r = 2.5, \quad \tan \delta = 10^{-13}, \quad f = 4 \text{ GHz}, \quad \mu = \mu_0$$

$$u_p = \frac{1}{\sqrt{2.5 \epsilon_0 \mu_0}} = 1.897 \times 10^8 \text{ m/s} \quad \eta = \sqrt{\frac{\mu_0}{2.5 \epsilon_0}} = 238.32 \, \Omega$$

$$f_{c10} = \frac{1.897 \times 10^8}{2 \times 0.03} = 3.16 \times 10^9 \text{ Hz}$$

$$\text{Skin depth: } \delta_c = \frac{1}{\sqrt{5.76 \times 10^7 \times 4\pi \times 10^{-7} \times 4 \times 10^9 \pi}} = 1.05 \times 10^{-6} \text{ m}$$

Conductivity of polyethylene:

$$\sigma_d = 2\pi \times 4 \times 10^9 \times 10^{-13} \times 2.5 \times 8.85 \times 10^{-12} = 5.56 \times 10^{-14} \text{ S/m}$$

$$\alpha_{c10} = \frac{\left[ 1 + \frac{2 \times 0.02}{0.03} \left( \frac{3.16}{4} \right)^2 \right]}{5.76 \times 10^7 \times 1.05 \times 10^{-6} \times 238.32 \times 0.02 \sqrt{1 - \left( \frac{3.16}{4} \right)^2}} = 1.037 \times 10^{-2} \text{ Np/m}$$

$$\alpha_{d10} = \frac{1}{2} \times 5.56 \times 10^{-14} \times 238.32 \sqrt{1 - \left( \frac{3.16}{4} \right)^2} = 4.06 \times 10^{-12} \text{ Np/m}$$

### Exercise 10.9

$$\delta_c = \frac{1}{\sqrt{\pi \times 6.25 \times 10^9 \times 3.55 \times 10^7 \times 4\pi \times 10^{-7}}} = 1.068 \times 10^{-6} \text{ m}$$

$$\text{for } \sigma_c = 3.55 \times 10^7 \text{ S/m} \quad Q \approx 4577$$



### Exercise 10.10

$$a = 2 \text{ cm}, b = 1 \text{ cm}, c = 4 \text{ cm}, \text{ TM}_{101}$$

$$f_{101} = \frac{1}{2\sqrt{\mu_0 \epsilon_0}} \sqrt{\left(\frac{1}{0.02}\right)^2 + \left(\frac{1}{0.04}\right)^2} = 8.385 \times 10^9 \text{ Hz}$$

$$\delta_c = \frac{1}{\sqrt{5.8 \times 10^7 \times 4\pi \times 10^{-7} \times 8.385 \times 10^9 \pi}} = 7217 \times 10^{-7} \text{ m}$$

From Eq. (10.124)

$$Q = 7299$$

From Eq. (10.123)

$$P_{\text{av}} = 4.539 \times 10^{-5} \text{ W}$$

# Problem 10.5

$$a = 4, \quad b = 3 \text{ cm}, \quad f = 20 \text{ GHz}, \quad E_{zm} = 600 \text{ V/m} \quad \text{TM}_{11}$$

$$a) \quad f_{c11} = \frac{3 \times 10^8}{2} \sqrt{\left(\frac{1}{0.04}\right)^2 + \left(\frac{1}{0.03}\right)^2} = 6.25 \times 10^9 \text{ Hz}$$

$$\beta_{11} = \frac{2\pi \times 20 \times 10^9}{3 \times 10^8} \sqrt{1 - \left(\frac{6.25}{20}\right)^2} = 397.9 \text{ rad/m}$$

$$b) \quad x = 1 \text{ cm}, \quad y = 1.5 \text{ cm}, \quad z = 50 \text{ cm}$$

$$\tilde{E}_z = 600 \sin\left(\frac{\pi}{4}x\right) \sin\left(\frac{\pi}{3}y\right) e^{-397.9 \times 0.5}$$

$$\tilde{E}_z = \sqrt{2} \times 30 e^{-j198.95} \text{ V/m}$$

$$\tilde{E}_y = - \frac{j 397.9 \pi \times 600}{\left[\left(\frac{\pi}{0.04}\right)^2 + \left(\frac{\pi}{0.03}\right)^2\right] 0.03} \sin\left(\frac{\pi}{4}x\right) \cos\left(\frac{\pi}{3}y\right) e^{-j397.9 \times 0.5}$$

$$\tilde{E}_y = 0$$

$$\tilde{E}_x = - \frac{j 397.9 \pi \times 600}{\left[\left(\frac{\pi}{0.04}\right)^2 + \left(\frac{\pi}{0.03}\right)^2\right] 0.04} \cos\left(\frac{\pi}{4}x\right) \sin\left(\frac{\pi}{3}y\right) e^{-j397.9 \times 0.5}$$

$$\tilde{E}_x = 14.93 e^{-j(198.95 + \frac{\pi}{2})} \text{ V/m}$$

$$\tilde{H}_x = j \frac{2\pi \times 20 \times 10^9 \pi \times 600 \times \epsilon_0}{\left[\left(\frac{\pi}{0.04}\right)^2 + \left(\frac{\pi}{0.03}\right)^2\right] 0.03} \sin\left(\frac{\pi}{4}x\right) \cos\left(\frac{\pi}{3}y\right) e^{-j397.9 \times 0.5}$$

$$\tilde{H}_x = 0$$

$$\tilde{H}_y = -j \frac{2\pi \times 20 \times 10^9 \pi \times 600 \epsilon_0}{\left[ \left( \frac{\pi}{0.04} \right)^2 + \left( \frac{\pi}{0.03} \right)^2 \right]^{0.04}} \cos\left(\frac{\pi}{4} \times 1\right) \sin\left(\frac{\pi}{3} \times 1.5\right) e^{-397.9 \times 0.5}$$

$$\tilde{H}_y = 2.16 e^{-j(198.95 + \frac{\pi}{2})} \text{ A/m}$$

$$\tilde{H}_z = 0$$

### Problem 10.6

$$a = 2 \text{ cm}, \quad f = 12 \text{ GHz}, \quad \text{TM}_{11}$$

$$a) \quad f_{c11} = \frac{3 \times 10^8}{2} \sqrt{\left( \frac{1}{0.02} \right)^2 + \left( \frac{1}{0.02} \right)^2} = 10.61 \text{ GHz}$$

$$b) \quad \lambda = \frac{3 \times 10^8}{12 \times 10^9} = 0.25 \times 10^{-1} \text{ m}$$

$$\lambda_{c11} = \frac{3 \times 10^8}{10.61 \times 10^9} = 2.83 \times 10^{-2} \text{ m}$$

$$c) \quad \lambda_{11} = \frac{2.5 \times 10^{-2}}{\sqrt{1 - \left( \frac{10.61}{12} \right)^2}} = 0.0535 \text{ m} \quad \text{or} \quad 5.35 \text{ cm}$$

$$d) \quad u_{p11} = \frac{3 \times 10^8}{\sqrt{1 - \left( \frac{10.61}{12} \right)^2}} = 6.42 \times 10^8 \text{ m/s}$$

$$e) \quad u_{g11} = 3 \times 10^8 \sqrt{1 - \left( \frac{10.61}{12} \right)^2} = 1.4 \times 10^8 \text{ m/s}$$

$$\beta_{11} = \frac{2\pi \times 12 \times 10^9}{3 \times 10^8} \sqrt{1 - \left( \frac{10.61}{12} \right)^2} = 117.4 \text{ rad/m}$$

$$M = N = \frac{\pi}{2 \times 10^{-2}} = 50\pi$$

$$\tilde{E}_z = \hat{E}_{zm} \sin(50\pi x) \sin(50\pi y) e^{-j117.4z}$$

$$\tilde{E}_x = \frac{-j117.4}{2 \times (50\pi)^2} 50\pi \hat{E}_{zm} \cos(50\pi x) \sin(50\pi y) e^{-j117.4z}$$

$$\tilde{E}_x = -j0.374 \hat{E}_{zm} \cos(50\pi x) \sin(50\pi y) e^{-j117.4z}$$

$$\tilde{H}_x = \frac{j 2\pi \times 12 \times 10^9 \times 8.85 \times 10^{-12}}{2 \times (50\pi)^2} 50\pi \hat{E}_{zm} \sin(50\pi x) \cos(50\pi y) e^{-j117.4z}$$

$$\tilde{H}_x = j2.124 \times 10^{-3} \hat{E}_{zm} \sin(50\pi x) \cos(50\pi y) e^{-j117.4z}$$

$$\tilde{H}_y = - \frac{j 2\pi \times 12 \times 10^9 \times 8.85 \times 10^{-12}}{2 \times (50\pi)^2} 50\pi \hat{E}_{zm} \cos(50\pi x) \sin(50\pi y) e^{-j117.4z}$$

$$\tilde{H}_y = -j2.124 \times 10^{-3} \hat{E}_{zm} \cos(50\pi x) \sin(50\pi y) e^{-j117.4z}$$

### Problem 10.7

$$f = 3 \text{ GHz}, \quad u_g = 2 \times 10^8 \text{ m/s}, \quad \epsilon = 2\epsilon_0$$

$$u_p = \frac{1}{\sqrt{2\epsilon_0\mu_0}} = 2.12 \times 10^8 \text{ m/s}$$

$$2 \times 10^8 = 2.12 \times 10^8 \sqrt{1 - \left(\frac{f_{c10}}{3 \times 10^9}\right)^2} \Rightarrow f_{c10} = 9.95 \times 10^8 \text{ Hz}$$

$$f_{c10} = \frac{2.12 \times 10^8}{2a} = 9.95 \times 10^8 \Rightarrow a = 0.1065 \text{ m} \quad a = 10.65 \text{ cm}$$

Problem 10.8

$$b = 1 \text{ cm}, \quad \tilde{E}_y = -j100 \sin\left(\frac{\pi x}{a}\right) e^{-j\beta_{10}z}$$

$$\tilde{H}_x = j0.1 \sin\left(\frac{\pi x}{a}\right) e^{-j\beta_{10}z}$$

$$f = 10 \text{ GHz}, \quad \text{TE}_{10}$$

$$\eta_{\text{TE}} = -\frac{\tilde{E}_y}{\tilde{H}_x} = -\frac{-j100}{j0.1} = 1000 \Omega$$

$$1000 = \frac{377}{\sqrt{1 - \left(\frac{f_{c10}}{f}\right)^2}} \Rightarrow f_{c10} = 9.26 \text{ GHz}$$

$$f_{c10} = \frac{u_p}{2a} \quad a = \frac{3 \times 10^8}{2 \times 9.26 \times 10^9} = 0.0162 \text{ m} \quad a = 1.62 \text{ cm}$$

$$\beta_{10} = \frac{2\pi \times 10^{10}}{3 \times 10^8} \sqrt{1 - \left(\frac{9.26}{10}\right)^2} = 79.07 \text{ rad/m}$$

$$\frac{\beta_{10} H_{zm}}{\pi} = H_{xm} \Rightarrow H_{zm} = \frac{0.1 \pi}{79.07 \times 0.0162} = 0.245 \text{ A/m}$$

$$\tilde{H}_z = 0.245 \cos\left(\frac{\pi x}{a}\right) e^{-j\beta_{10}z}, \quad \tilde{H}_y = 0, \quad \tilde{E}_x = 0, \quad \tilde{E}_z = 0$$

$$E_y(t) = 100 \sin(193.92x) \cos(2\pi \times 10^{10}t - 79.07z - \frac{\pi}{2})$$

$$H_x(t) = 0.1 \sin(193.92x) \cos(2\pi \times 10^{10}t - 79.07z + \frac{\pi}{2})$$

$$H_z(t) = 0.245 \cos(193.92x) \cos(2\pi \times 10^{10}t - 79.07z)$$

$$\langle P_{10} \rangle_{z=0} = \frac{2\pi \times 10^{10} \times 4\pi \times 10^{-7} \times 0.0162^3 \times 0.01}{4\pi^2} \times 79.07 \times 0.245^2 = 4.04 \times 10^{-4} \text{ W}$$

### Problem 10.9

$$\beta_{z1} = 165 \text{ rad/m} \quad TM_{z1} \quad f = 1.1 f_{c21}$$

$$165 = \frac{2\pi \times 1.1 f_{c21}}{3 \times 10^8} \sqrt{1 - \left( \frac{f_{c21}}{1.1 f_{c21}} \right)^2} \Rightarrow f_{c21} = 17.17 \text{ GHz}$$

$$f = 1.1 \times 17.17 = 18.89 \text{ GHz}$$

$$\lambda_{z1} = \frac{2\pi \times 3 \times 10^8}{2\pi \times 18.89 \times 10^9} \frac{1}{\sqrt{1 - \left( \frac{17.17}{18.89} \right)^2}} = 6.616 \times 10^{-3} \text{ m}$$

$$\lambda_{z1} = 6.616 \text{ mm}$$

### Problem 10.10

$$E = 500 \text{ V/m}, \quad TE_{10}, \quad f = 10 \text{ GHz}, \quad l = 2 \text{ m}, \quad a = 3 \text{ cm}, \quad b = 2 \text{ cm}$$

$$f_{c10} = \frac{3 \times 10^8}{2 \times 0.03} = 5 \times 10^9 \text{ Hz}$$

$$\eta_{TE_{10}} = \frac{377}{\sqrt{1 - \left( \frac{5}{10} \right)^2}} = 435.32 \Omega$$

$$\langle S_{10} \rangle = \frac{1}{2} \frac{500^2 \sin^2\left(\frac{\pi}{a}x\right)}{435.32} \bar{a}_z = 287.15 \sin^2\left(\frac{\pi}{a}x\right) \text{ W/m}^2$$

$$\langle P_{10} \rangle = \int_0^b \int_0^a 287.15 \sin^2\left(\frac{\pi}{a}x\right) dx dy = 287.15 \frac{1}{2} ab$$

$$= \frac{1}{2} 287.15 \times 0.03 \times 0.02 = 8.614 \times 10^{-2} \text{ W}$$

$$\langle P_{10} \rangle = 86.14 \text{ mW}$$

$$\tilde{H}_y = 0, \quad \tilde{E}_x = 0, \quad \tilde{E}_z = 0 \quad \beta_{10} = \frac{2\pi \times 10^{10}}{3 \times 10^8} \sqrt{1 - \left(\frac{5}{10}\right)^2} = 181.38 \text{ rad/m}$$

$$\tilde{E}_y = 500 \sin\left(\frac{\pi}{0.03}x\right) e^{-j181.38z}$$

$$\tilde{E}_y = 500 \sin(33.33\pi x) e^{-j181.38z}$$

$$E_y(t) = 500 \sin(33.33\pi x) \cos(2\pi \times 10^{10}t - 181.38z) \quad \text{V/m}$$

$$-j \frac{2\pi \times 10^{10} \times 4\pi \times 10^{-7} \times 0.03}{\pi} \hat{H}_{zm} = 500$$

$$\hat{H}_{zm} = \frac{500\pi}{-j 2\pi \times 10^{10} \times 4\pi \times 10^{-7} \times 0.03} = j0.663 \text{ A/m}$$

$$\tilde{H}_z = j0.663 \cos(33.33\pi x) e^{-j181.38z}$$

$$H_z(t) = 0.663 \cos(33.33\pi x) \cos(2\pi \times 10^{10}t - 181.38z + \frac{\pi}{2}) \quad \text{A/m}$$

$$\tilde{H}_x = j \frac{181.38 \times 0.03}{\pi} (j0.663) \sin(33.33\pi x) e^{-j181.38z}$$

$$\tilde{H}_x = -1.15 \sin(33.33\pi x) e^{-j181.38z}$$

$$H_x(t) = 1.15 \sin(33.33\pi x) \cos(2\pi \times 10^{10}t - 181.38z + \pi) \quad \text{A/m}$$

### Problem 10.11

$$a = 2 \text{ cm}, \quad b = 1 \text{ cm} \quad f_{c10} = \frac{3 \times 10^8}{2 \times 2 \times 10^{-2}} = 7.5 \times 10^9 \text{ Hz}$$

$$f_{c11} = \frac{3 \times 10^8}{2} \sqrt{\frac{1}{0.02^2} + \frac{1}{0.01^2}} = 16.77 \times 10^9 \text{ Hz}$$

$$\text{Frequency range for TE}_{10} : 7.5 \text{ GHz} < f < 16.77 \text{ GHz}$$

### Problem 10.12

$$a = 2 \text{ cm}, \quad b = 3 \text{ cm} \quad \epsilon_r = 3 \quad f = 50 \text{ GHz} \quad \text{TE}_{22}$$

$$u_p = \frac{1}{\sqrt{3\epsilon_0\mu_0}} = \frac{3 \times 10^8}{\sqrt{3}} = \sqrt{3} \times 10^8 \text{ m/s}$$

$$f_{c22} = \frac{\sqrt{3} \times 10^8}{2} \sqrt{\left(\frac{2}{0.02}\right)^2 + \left(\frac{2}{0.03}\right)^2} = 10.4 \text{ GHz}$$

$$\lambda_{22} = \frac{2\pi \sqrt{3} \times 10^8}{2\pi \times 50 \times 10^9} \frac{1}{\sqrt{1 - \left(\frac{10.4}{50}\right)^2}} = 3.54 \times 10^{-3} \text{ m} \quad \text{or} \quad 3.54 \text{ mm}$$

$$\beta_{22} = \frac{2\pi \times 50 \times 10^9}{\sqrt{3} \times 10^8} \sqrt{1 - \left(\frac{10.4}{50}\right)^2} = 1774.13 \text{ rad/m}$$

$$u_{p22} = \frac{\sqrt{3} \times 10^8}{\sqrt{1 - \left(\frac{10.4}{50}\right)^2}} = 1.77 \times 10^8 \text{ m/s}$$

$$u_{g22} = \sqrt{3} \times 10^8 \sqrt{1 - \left(\frac{10.4}{50}\right)^2} = 1.694 \times 10^8 \text{ m/s}$$

$$\eta_{22}^{\text{TE}} = \frac{\sqrt{\frac{4\pi \times 10^{-7}}{3 \times 8.85 \times 10^{-12}}}}{\sqrt{1 - \left(\frac{10.4}{50}\right)^2}} = 222.42 \, \Omega$$

$$M = \frac{2\pi}{0.02} = 100\pi \quad N = \frac{2\pi}{0.03} = 66.66\pi$$

$$\tilde{H}_x = \frac{j1774.13}{(100\pi)^2 + (66.66\pi)^2} \times 100\pi \hat{H}_{2m} \sin(100\pi x) \cos(66.66\pi y) e^{-j1774.13z}$$

$$\tilde{H}_x = j3.91 \hat{H}_{2m} \sin(100\pi x) \cos(66.66\pi y) e^{-j1774.13z}$$

$$H_x(t) = 3.91 H_{2m} \sin(100\pi x) \cos(66.66\pi y) \cos(2\pi \times 50 \times 10^9 t - 1774.13z + \theta_H + \frac{\pi}{2})$$



$$\tilde{H}_y = \frac{j1774.13}{(100\pi)^2 + (66.66\pi)^2} \times 66.66\pi \hat{H}_{zm} \cos(100\pi x) \sin(66.66\pi y) e^{-j1774.13z}$$

$$\tilde{H}_y = j2.61 \hat{H}_{zm} \cos(100\pi x) \sin(66.66\pi y) e^{-j1774.13z}$$

$$H_y(t) = 2.61 H_{zm} \cos(100\pi x) \sin(66.66\pi y) \cos(2\pi \times 5 \times 10^{10} t - 1774.13z + \theta_H + \frac{\pi}{2})$$

$$\tilde{E}_x = \frac{j2\pi \times 5 \times 10^{10} \times 4\pi \times 10^{-7}}{(100\pi)^2 + (66.66\pi)^2} 66.66\pi \hat{H}_{zm} \cos(100\pi x) \sin(66.66\pi y) e^{-j1774.13z}$$

$$\tilde{E}_x = j579.96 \hat{H}_{zm} \cos(100\pi x) \sin(66.66\pi y) e^{-j1774.13z}$$

$$E_x(t) = 579.96 H_{zm} \cos(100\pi x) \sin(66.66\pi y) \cos(2\pi \times 5 \times 10^{10} t - 1774.13z + \theta_H + \frac{\pi}{2})$$

$$\tilde{E}_y = -\frac{j2\pi \times 5 \times 10^{10} \times 4\pi \times 10^{-7}}{(100\pi)^2 + (66.66\pi)^2} (100\pi) \hat{H}_{zm} \sin(100\pi x) \cos(66.66\pi y) e^{-j1774.13z}$$

$$\tilde{E}_y = -j870.03 \hat{H}_{zm} \sin(100\pi x) \cos(66.66\pi y) e^{-j1774.13z}$$

$$E_y(t) = 870.03 H_{zm} \sin(100\pi x) \cos(66.66\pi y) \cos(2\pi \times 5 \times 10^{10} t - 1774.13z + \theta_H - \frac{\pi}{2})$$

$$\tilde{E}_z = 0$$

### Problem 10.13

$$a = 2 \text{ cm}, \quad b = 1 \text{ cm}, \quad TE_{10}, \quad f = 15 \text{ GHz}, \quad \langle P_{10} \rangle = 1 \text{ kW}$$

$$\langle P_{10} \rangle = \frac{1}{2} \frac{E^2}{\eta_{10}} ab, \quad f_{c_{10}} = \frac{3 \times 10^8}{2 \times 0.02} = 0.75 \times 10^{10} \text{ Hz}$$

$$f_{c_{10}} = 7.5 \text{ GHz}$$

$$\eta_{10} = \frac{377}{\sqrt{1 - (\frac{7.5}{15})^2}} = 435.32 \Omega$$

$$E^2 = \eta_{10} 2 \times 1000 \frac{1}{2 \times 10^{-2} \times 10^{-2}} \Rightarrow E = \sqrt{10^7 \eta_{10}}$$

835

$$E = \sqrt{10^7 \times 435.32} = 65.978 \text{ kV/m}$$

$$H = \frac{65.978}{435.32} = 151.56 \text{ A/m}$$

$$H_{zm} = \frac{151.56 \times \pi}{272.07 \times 0.02} = 87.5 \text{ A/m}$$

$$\tilde{H}_y = 0, \quad \tilde{E}_x = 0, \quad \tilde{E}_z = 0$$

$$\beta_0 = \frac{2\pi \times 15 \times 10^9}{3 \times 10^8} \sqrt{1 - \left(\frac{7.5}{15}\right)^2} = 272.07 \text{ rad/m}$$

$$\tilde{H}_x = j 151.56 \sin\left(\frac{\pi}{0.02} x\right) e^{-j 272.07 z}$$

$$\tilde{H}_x = j 151.56 \sin(50\pi x) e^{-j 272.07 z} e^{j \theta_H}$$

$$H_x(t) = 151.56 \sin(50\pi x) \cos(2\pi \times 15 \times 10^9 t - 272.07 z + \frac{\pi}{2} + \theta_H)$$

$$\tilde{H}_z = 87.5 \cos(50\pi x) e^{-j 272.07 z} e^{j \theta_H}$$

$$H_z(t) = 87.5 \cos(50\pi x) \cos(2\pi \times 15 \times 10^9 t - 272.07 z + \theta_H)$$

$$\tilde{E}_y = -j 65,978 \sin(50\pi x) e^{-j 272.07 z} e^{j \theta_E}$$

$$E_y(t) = 65,978 \sin(50\pi x) \cos(2\pi \times 15 \times 10^9 t - 272.07 z + \theta_E)$$

#### Problem 10.14

$$a = 3 \text{ cm}, \quad b = 1 \text{ cm}, \quad l = 1 \text{ m}, \quad f = 12 \text{ GHz}, \quad TE_{10}$$

$$\tan \delta = 10^{-4}, \quad \sigma = 5.8 \times 10^7 \text{ S/m}$$

$$f_{c10} = \frac{3 \times 10^8}{2 \times 0.03} = 5 \times 10^9 \text{ Hz}$$

$$\delta_c = \frac{1}{\sqrt{5.8 \times 10^7 \times 4\pi \times 10^{-7} \times 12 \times 10^9 \pi}} = 6.03 \times 10^{-7} \text{ m}$$

$$\sigma_d = \omega \epsilon \tan \delta = 2\pi \times 12 \times 10^9 \times 8.85 \times 10^{-12} \times 10^{-4} = 6.67 \times 10^{-5} \text{ S/m}$$

$$\alpha_{c10} = \frac{1 + \frac{2 \times 0.01}{0.03} \left( \frac{5}{12} \right)^2}{5.8 \times 10^7 \times 6.03 \times 10^{-7} \times 377 \times 0.01 \sqrt{1 - \left( \frac{5}{12} \right)^2}} = 9.308 \times 10^{-3} \text{ Np/m}$$

$$\alpha_{d10} = \frac{6.67 \times 10^{-5}}{2} \times 377 \sqrt{1 - \left( \frac{5}{12} \right)^2} = 1.143 \times 10^{-2} \text{ Np/m}$$

Problem 10.15

$$E_m = 800 \text{ V/m}, \quad f = 12 \text{ GHz}$$

$$\langle P_d \rangle = \frac{H_{zm}^2}{\sigma_c \delta_c} \left[ b + \frac{a}{2} \left( \frac{f}{f_{c10}} \right)^2 \right] e^{-2\alpha_{10} z}$$

$$\alpha_{10} = \alpha_{c10} + \alpha_{d10} = 9.308 \times 10^{-3} + 1.143 \times 10^{-2} = 2.074 \times 10^{-2} \text{ Np/m}$$

$$E_{ym} = \frac{a \omega \mu H_{zm}}{\pi} \Rightarrow H_{zm} = \frac{800 \pi}{2\pi \times 12 \times 10^9 \times 4\pi \times 10^{-7} \times 0.03} = 0.884 \text{ A/m}$$

$$\langle P_d \rangle = \frac{0.884^2}{5.8 \times 10^7 \times 6.03 \times 10^{-7}} \left[ 0.01 + \frac{0.03}{2} \left( \frac{12}{5} \right)^2 \right] e^{-2 \times 2.074 \times 10^{-2} \times z}$$

$$P_{dT} = \int_0^l P_d e^{-2\alpha_{10} z} dz = \frac{2.15 \times 10^{-3}}{2 \times 2.074 \times 10^{-2}} (1 - e^{-2 \times 2.074 \times 10^{-2} \times l})$$

$$P_{dT} = 2.1 \times 10^{-3} \text{ W} \quad \text{or} \quad 2.1 \text{ mW}$$

At  $x=0$  wall :

$$\vec{J}_s = -H_{zm} e^{-j\beta_{10}z} e^{-\alpha_{c10}z} \vec{a}_y$$

$$\beta_{10} = \frac{2\pi \times 12 \times 10^9}{3 \times 10^8} \sqrt{1 - \left(\frac{5}{12}\right)^2} = 228.47 \text{ rad/m}$$

$$\vec{J}_s = -0.884 \times e^{-j228.47z} e^{-9.308 \times 10^{-3}z} \vec{a}_y$$

$$\vec{J}_s = -0.884$$

At  $y=0$  wall :

$$\vec{J}_s = -j \frac{228.47 \times 0.03}{\pi} 0.884 \sin\left(\frac{\pi}{0.03}x\right) e^{-j228.47z} e^{-9.308 \times 10^{-3}z} \vec{a}_z$$

$$+ 0.884 \cos\left(\frac{\pi}{0.03}x\right) e^{-j228.47z} e^{-9.308 \times 10^{-3}z} \vec{a}_x$$

$$\vec{J}_s = -j1.93 \sin(33.33\pi x) e^{-j228.47z} e^{-9.308 \times 10^{-3}z} \vec{a}_z$$

$$+ 0.884 \cos(33.33\pi x) e^{-j228.47z} e^{-9.308 \times 10^{-3}z} \vec{a}_x$$

At  $x=0$  wall :  $\vec{J}_s = 0$

At  $y=0$  wall :  $\vec{P}_s = -j \frac{\omega \mu a}{\pi} \epsilon_0 H_{zm} \sin(33.33\pi x) e^{-j228.47z} e^{-9.308 \times 10^{-3}z}$

$$\vec{P}_s = -j \frac{2\pi \times 12 \times 10^9 \times 4\pi \times 10^{-7} \times 0.03}{\pi} \times 8.85 \times 10^{-12} \times 0.884 \sin(33.33\pi x) e^{-j228.47z} e^{-9.308 \times 10^{-3}z}$$

$$\vec{P}_s = -j 7.08 \times 10^{-9} \sin(33.33\pi x) e^{-j228.47z} e^{-9.308 \times 10^{-3}z} \text{ C/m}^2$$

### Problem 10.16

$$l = 10 \text{ m}, \quad a = 4 \text{ cm}, \quad b = 3 \text{ cm}, \quad TE_{10}, \quad f = 4 \text{ GHz}, \quad E = 1000 \text{ V/m}$$

$$\tan \delta = 10^{-4}, \quad \sigma = 5.8 \times 10^{-7} \text{ S/m}$$

$$f_{c_{10}} = \frac{3 \times 10^8}{2 \times 0.04} = 3.75 \times 10^9 \text{ Hz} \quad f_{c_{10}} = 3.75 \text{ GHz}$$

$$\delta_c = \frac{1}{\sqrt{5.8 \times 10^{-7} \times 4\pi \times 10^{-7} \times 4 \times 10^9 \pi}} = 1.045 \times 10^{-6} \text{ m}$$

$$\alpha_{c_{10}} = \frac{1}{5.8 \times 10^{-7} \times 1.045 \times 10^{-6} \times 377 \times 0.03} \frac{\left[ 1 + \frac{2 \times 0.03}{0.04} \left( \frac{3.75}{4} \right)^2 \right]}{\sqrt{1 - \left( \frac{3.75}{4} \right)^2}}$$

$$\alpha_{c_{10}} = 9.718 \times 10^{-3} \text{ Np/m}$$

$$\sigma_d = \omega \epsilon \tan \delta = 2\pi \times 4 \times 10^9 \times 8.85 \times 10^{-12} \times 10^{-4}$$

$$\sigma_d = 2.224 \times 10^{-5} \text{ S/m}$$

$$\alpha_{d_{10}} = \frac{2.224 \times 10^{-5}}{2} \times 377 \sqrt{1 - \left( \frac{3.75}{4} \right)^2} = 1.459 \times 10^{-3} \text{ Np/m}$$

$$\alpha_{10} = \alpha_{c_{10}} + \alpha_{d_{10}} = 9.718 \times 10^{-3} + 1.459 \times 10^{-3} = 11.18 \times 10^{-3} \text{ Np/m}$$

$$H_{zm} = \frac{1000 \pi}{2\pi \times 4 \times 10^9 \times 4\pi \times 10^{-7} \times 0.04} = 2.49 \text{ A/m}$$

$$\beta_{10} = \frac{2\pi \times 4 \times 10^9}{3 \times 10^8} \sqrt{1 - \left( \frac{3.75}{4} \right)^2} = 29.15 \text{ rad/m}$$

$$\langle P_{10} \rangle_z = \frac{2\pi \times 4 \times 10^9 \times 4\pi \times 10^{-7} \times 0.04^3 \times 0.03}{4\pi^2} 29.15 \times 2.49^2 e^{-2 \times 11.18 \times 10^{-3} \times 10}$$

$$\langle P_{10} \rangle_z = 0.222 \text{ W}$$

### Problem 10.17

$$E = 800 \text{ V/m}, \text{ TE}_{10}, f = 4 \text{ GHz}$$

$$\langle P_d \rangle = P_d e^{-2\alpha_{10}z}$$

$$P_{dT} = \int_0^l P_d e^{-2\alpha_{10}z} dz = P_d \frac{1}{2\alpha_{10}} (1 - e^{-2\alpha_{10}l})$$

$$H_{zm} = \frac{800\pi}{2\pi \times 4 \times 10^9 \times 4\pi \times 10^{-7} \times 0.04} = 1.99 \text{ A/m}$$

$$P_d = \frac{1.99^2}{5.8 \times 10^7 \times 1.045 \times 10^{-6}} \left[ 0.03 + \frac{0.04}{2} \left( \frac{4}{3.75} \right)^2 \right] = 3.44 \times 10^{-3} \text{ W/m}$$

$$P_{dT} = 3.44 \times 10^{-3} \frac{1}{2 \times 11.18 \times 10^{-3}} (1 - e^{-2 \times 11.18 \times 10^{-3} \times 10})$$

$$P_{dT} = 3.09 \times 10^{-2} \text{ W}$$

### Problem 10.18

$$a = 5 \text{ cm}, b = 2 \text{ cm}, l = 7 \text{ cm}, \text{ TM}_{110}$$

$$f_{110} = \frac{1}{2 \sqrt{4\pi \times 10^{-7} \times 8.85 \times 10^{-12}}} \sqrt{\left( \frac{1}{0.05} \right)^2 + \left( \frac{1}{0.02} \right)^2}$$

$$f_{110} = 8.07 \times 10^9 \text{ Hz} \quad \text{or} \quad 8.07 \text{ GHz.}$$

Problem 10.19

$$f = 9 \text{ GHz}, \text{ TE}_{101}$$

$$f_{101} = \frac{1}{2 \sqrt{4\pi \times 10^{-7} \times 8.85 \times 10^{-12}}} \sqrt{\left(\frac{1}{a}\right)^2 + \left(\frac{1}{a}\right)^2} = 9 \times 10^9$$

$$a = 2.36 \times 10^{-2} \text{ m} \quad \text{or} \quad 2.36 \text{ cm}$$

Problem 10.20

$$a = 3 \text{ cm}, \quad b = 1 \text{ cm}, \quad l = 5 \text{ cm}, \quad \sigma = 5.8 \times 10^7 \text{ S/m}, \quad \text{TE}_{101}$$

$$a) \quad f_{101} = \frac{1}{2 \sqrt{4\pi \times 10^{-7} \times 8.85 \times 10^{-12}}} \sqrt{\frac{1}{0.03^2} + \frac{1}{0.05^2}} = 5.83 \times 10^9 \text{ Hz}$$

$$b) \quad \delta_c = \frac{1}{\sqrt{5.8 \times 10^7 \times 4\pi \times 10^{-7} \times 5.83 \times 10^9 \pi}} = 8.66 \times 10^{-7} \text{ m}$$

$$Q = \frac{4\pi (5.83 \times 10^9)^3 (0.05)^3 (0.03)^3 (4\pi \times 10^{-7})^2 (8.85 \times 10^{-12}) (0.01) (5.8 \times 10^7) \delta_c}{2 (0.03)^3 (0.01) + (0.03)^3 (0.05) + (0.03) (0.05)^3 + 2 \times 0.01 \times 0.05^2}$$

$$Q = 7243$$

$$c) \quad W = 2 \times 8.85 \times 10^{-12} \times 0.01 \times 0.05 \times 0.03^3 \times (5.83 \times 10^9)^2 (4\pi \times 10^{-7})^2 \times 2^2$$

$$W = 5.13 \times 10^{-11} \text{ J}$$

### Problem 10.21

$$C = 1 \text{ pF} \quad Q = \frac{\omega L}{R} \quad \omega = \frac{1}{\sqrt{LC}}$$

$$L = \frac{1}{(2\pi \times 5.83 \times 10^9)^2 \times 10^{-12}} = 7.45 \times 10^{-10} \text{ H} \quad L = 0.745 \text{ nH}$$

$$7243 = \frac{2\pi \times 5.83 \times 10^9 \times 7.45 \times 10^{-10}}{R} \Rightarrow R = 3.77 \times 10^{-3} \Omega \text{ or } 3.77 \text{ m}\Omega$$

It is almost impractical to realize such a lumped circuit.

### Problem 10.22

$$f = 106 \text{ Hz}, \text{ TE}_{101}$$

$$10 \times 10^9 = \frac{3 \times 10^8}{2} \sqrt{2 \frac{1}{a^2}} \Rightarrow a = 2.12 \times 10^{-2} \text{ m} \\ a = 2.12 \text{ cm}$$

### Problem 10.23

$$a = 2 \text{ cm}, b = 3 \text{ cm}, l = 5 \text{ cm}, \text{ TE}_{101} \\ \sigma_{\text{cu}} = 5.8 \times 10^7 \text{ S/m} \quad \sigma_{\text{Al}} = 3.5 \times 10^7 \text{ S/m}$$

$$f_{101} = \frac{3 \times 10^8}{2} \sqrt{\left(\frac{1}{0.02}\right)^2 + \left(\frac{1}{0.05}\right)^2} = 8.08 \times 10^9 \text{ Hz}$$

For Copper:

$$\delta_c = \frac{1}{\sqrt{5.8 \times 10^7 \times 4\pi \times 10^{-7} \times 8.08 \times 10^9 \pi}} = 7.35 \times 10^{-7} \text{ m}$$



$$Q = \frac{4\pi(8.08 \times 10^9)^3 (0.05)^3 (0.02)^3 (4\pi \times 10^{-7})^2 (8.85 \times 10^{-12}) (0.03) (5.8 \times 10^7) (7.35 \times 10^{-7})}{2(0.02)^3 (0.03) + (0.02)^3 (0.05) + (0.02)(0.05)^3 + 2 \times 0.03 \times 0.05^3}$$

$$Q = 10890$$

$$W = 2 \times 8.85 \times 10^{-12} \times 0.03 \times 0.05 \times 0.02^3 \times (8.08 \times 10^9)^2 (4\pi \times 10^{-7})^2 \times H_{zm}^2$$

$$W = 2.19 \times 10^{-11} H_{zm}^2$$

For aluminum:

$$\delta_c = \frac{1}{\sqrt{3.5 \times 10^7 \times 4\pi \times 10^{-7} \times 8.08 \times 10^9 \pi}} = 9.46 \times 10^{-7} \text{ m}$$

$$Q = \frac{4\pi(8.08 \times 10^9)^3 (0.05)^3 (0.02)^3 (4\pi \times 10^{-7})^2 (8.85 \times 10^{-12}) (0.03) (10^7) (9.46 \times 10^{-7})}{2(0.02)^3 (0.03) + (0.02)^3 (0.05) + (0.02)(0.05)^3 + 2 \times 0.03 \times 0.05^3}$$

$$Q = 8462$$

$$W = 2.19 \times 10^{-11} H_{zm}^2$$

### Problem 10.24

$$f_{101} = 20 \text{ GHz} \quad \epsilon_r = 2.5$$

$$20 \times 10^9 = \frac{1}{2 \sqrt{2.5 \times 8.85 \times 10^{-12} \times 4\pi \times 10^{-7}}} \sqrt{2 \frac{1}{a^2}}$$

$$a = 6.7 \times 10^{-3} \text{ m} \quad a = 6.7 \text{ mm}$$